

Step 1: Wireless Setup

1. From EasyTouch control panel press **Menu**.
2. Press **Down button** - Select "Settings".
3. Press **Right button**.
4. Press **Up button** up to "Wireless Address".
5. Press **Right button** to select.
"Address Wireless scanning" will display.
Then "Sending Address" will display.
6. Repeat steps 1-5 from wireless handheld.
"Address Found" will display.
7. Press **Menu button** on control panel 3 times to return to Main screen.

Step 2: Clock, Set Time and Date

1. Press **Menu button**.
2. Press **Down button** to "Settings".
3. Press **Right button** 2 times (1 of 1/2 will blink).
4. Press **Right button** ("Month" blinks).
5. Press **Up/Down button** until desired month.
6. Press **Right button** to select ("Day" blinks).
7. Press **Up/Down button** until desired date is displayed.
8. Press **Right button** to select ("Year" blinks).
9. Press **Up button** to scroll to desired year.
10. Press **Right button** to select ("Day" blinks).
11. Press **Up/Down button** until desired day blinks.
12. Press **Right button** to select (Hour will blink).
13. Press **Up/Down button** until desired hour blinks.
14. Press **Right button** to select (Minutes will blink).
15. Press **Up/Down button** until desired minute blinks.
16. Press **Right button** to select (AM/PM will blink).
17. Press **Up/Down button** until desired AM/PM blinks.
18. Press **Right button** to select (1 of 1/2 will blink).
19. Press **Up/Down button** until 2/2 blinks.
20. Press **Right button** ("MAN" LED will blink).
21. Press **Up/Down button** until "AUTO" LED blinks.
22. Press **Right button** to select.
23. Press **Menu button** 3 times (return to Main screen).

Step 3: Assigning Circuit Names

- Circuit # 1-10 do not correlate with Aux buttons.
 - Circuit # 1 is ALWAYS SPA including POOL ONLY SYSTEMS - Circuit #2 is ALWAYS POOL.
 - Circuit #3 is AUX#1.
 - Circuit #4 is Aux #2, etc.
1. Press **Menu button**.
 2. Press **Down button** to "Settings".
 3. Press **Right button** to select.
 4. Press **Down button** to "Circuit Names".
 5. Press **Right button** to select (circuit 1 in 1/10 blink).
 6. Press **UP button** 2 times (3 in 3/10 will blink).
 7. Press **Right button** (Aux 1 will blink).
 8. Press **Up/Down button** to desired circuit name.
 9. Press **Right button** to select (3 in 3/10 will blink).
 10. Press **UP button** one time (4 of 4/10 will blink).
 11. Press **Right button** one time.
 12. Press **UP button** to desired circuit name.
 13. Press **Right button** to select (4 of 4/10 will blink).
- Repeat steps for each circuit name.

Step 4: Assigning Circuit Types

Booster Cleaner:

1. Press **Menu**, then **Down button** to "Settings".
3. Press **Right button** to select.
4. Press **Down button** to "Circuit types".
5. Press **Right button** (SPA will blink).
6. Press **Up button** 2 times (CLEANER will blink).
(If circuit 3-Aux 1 has already been named as the cleaner circuit.)
7. Press **Right button** to select (GENERIC will blink).
8. Press **Up button** 3 times to Cleaner or Mstr Cleaner.
9. Press **Menu button** 3 times to return to Main screen.

For Valve operated water feature:

1. Press **Menu**, then **Down button** to "Settings".
2. Press **Right button**.
3. Press **Down button** to valves (Aux 1 will blink).
4. Press **Up/Down button** to pre-named water feature circuit.
5. Press **Right button** to select.
6. Press **Menu button** 3 times to return to Main screen.

Note: FREEZE protect the pool circuit only!

Spillway:

1. Press **Menu**, then **Down button** to "Settings".
2. Press **Right button** to select.
3. Press **Down button** to "Circuit types".
4. Press **Right button** (SPA will blink).
5. Press **Up button** to Spillway circuit. (You must have already assigned spillway in circuit names.)
6. Press **Right button** (GENERIC will blink).
7. Press **Up button** to spillway.
8. Press **Right button** (NO will blink).
9. Press **Menu button** 3 times to return to Main screen.

Step 5: Setup IntelliFlo 4 x 160 Pump

1. Press **Menu** then **Down button** to "Settings".
 2. Press **Right button**.
 3. Press **Down button** to "IntelliFlo 4".
 4. Press **Right button** to select 1 of 1/4 will blink.
 5. Press **Right button** to select 750 will blink.
 6. Select speed using **Up/Down button**.
 7. Press **Right button** when desired speed is reached (NONE will blink).
 8. Press **Up/Down button** to desired circuit to match speed.
 9. Press **Right button** to select (1 of 1/4 will blink).
- Repeat steps 1-9 for each circuit that requires a custom speed.
10. Press **Menu button** 3 times to return to Main screen.

Step 6: Setup Schedules

1. Press **Menu button**.
2. Press **Down button** to schedules.
3. Press **Right button** to select:
See "Pool & Spa Combo and Pool Only".

(continued on backside)

Pool and Spa Combo

1. Press **Right button** to select Spa if a run time is desired for spa, if no run time is desired, then;
2. Press **Menu button**.
3. Press **Down button** to "Pool" and repeat steps.
4. Press **Right button** (NONE will blink).
5. Press **Up button** (NEW will blink).
6. Press **Right button** (1 in 1/1 will blink).
7. Press **Right button** 2 times (HOUR "8" will blink).
8. Press **Up button** to desired Start time.
9. Press **Right button** to select (MIN will blink).
Select Minutes if desired.
10. Press **Right button** (Stop hour will blink).
11. Press **Up/Down button** to desired stop hour.
12. Press **Right button** (MIN will blink).
13. Press **Up/Down button** to desired minute.
14. Press **Right button** to select (S will blink).

Note: If run time is the same everyday of the week Press Menu. Repeat steps for run times for remaining circuits if desired.

Pool Only

1. Press **Down button** to "POOL".
2. Press **Right button** (NONE will blink).
3. Press **Up button** (NEW will blink).
4. Press **Right button** (1 in 1/1 will blink).
5. Press **Right button** 2 times (Hour "8" will blink).
6. Press **Up button** to desired start time.
7. Press **Right button** to select (MIN will blink).
Select Minutes if desired.
8. Press **Right button** (STOP HOUR will blink).
9. Press **Right button** (MIN will blink).
10. Press **Up/Down button** to desired minute.
11. Press **Right button** to select (S will blink).

Note: If run time is the same for everyday of the week Press Menu. Repeat Steps 1-11 for run times for remaining circuits if desired.

Step 7: IntelliChlor

1. Press **Down button** to "POOL".
 2. Press **Right button**.
 3. Press **Down button** to "IntelliChlor".
 4. Press **Right button** (1 of 1/2 will blink).
- Note: Enable, should be set to "Yes".*
5. Press **Right button** until "Level 50%" blinks.
 6. Press **Up button** to increase or **Down button** to decrease chlorine output.
 7. Press **Right button** to save (1 of 1/2 will blink.)

To Superchlorinate:

1. Press **Up button** (2 of 2/2 will blink).
2. Press **Right button** (OFF will blink).
3. Press **Up button** (ON will blink).
4. Press **Right button** (24 will blink).
5. To Superchlorinate for 24 hours, press **Right button**. To increase or decrease hours of Superchlorination, press **Up/Down button**.
6. Press **Right button** to save.
7. Press **Menu button** 3 times - return to Main screen.

Step 8: Heater (if applicable)

1. Press **Menu button**.
2. Press **Down button** to "Heat".
3. Press **Right button** 2 times to heat pool.
4. Press **Up/Down button** to desired temperature (OFF will blink).
5. Press **Up/Down button** to "Heater".
6. Press **Right button** to save.
7. Press **Menu button** 3 times to return to Main screen.

Step 9: Solar (if applicable)

1. Press **Menu button**.
2. Press **Down button** to "Settings".
3. Press **Right button**.
4. Press **Down button** to "Solar".
5. Press **Right button** (1 of 1/2 will blink).
6. Press **Right button** (NO will blink).
7. Press **Up button** (YES will blink).
8. Press **Menu button** 3 times to Main screen.

TO ERASE MEMORY & START AGAIN

1. Press **Menu button**.
2. Press **Down button** to "Settings".
3. Press **Up button** to Erase EEPROM.
4. Press **Right button** ("NO" will blink).
5. Press **Up button** ("YES" will blink).
6. Press **Right button** to select ("NO" will blink).
7. Press **Up button** ("YES" will blink).
8. Press **Right button** to select, erase and restore default settings.

Manual Heat [On/Off]

1. Press **Menu button**.
2. Press **Down button** to "Settings".
3. Press **Right button** to select.
4. Press **Down button** to "MAN HEAT [ON/OFF]".
5. Press **Right button** to switch ON or OFF.
6. Press **Menu button** to return to Main screen.

iS4 Remote Controller

Note: Before configuring iS4 assign names to circuits, (see "Assigning Circuit Names").

1. Press **Menu button**.
2. Press **Down button** to "Settings".
3. Press **Right button** to select.
4. Press **Down button** to "iS4".
5. Press **Right button** to select "Assign iS4".
6. Press **Up button** (assign first circuit 1/4).
7. Press **Right button** (circuit setting).
8. Press **Up/Down button** to desired circuit name.
9. Press **Right button** to save.
10. Press **Right button** (assign next circuit 2/4).
11. Press **Up/Down button** to desired circuit name.
Repeat steps 6-8 to assign (3/4 and 4/4 circuits).
12. Press **Right button** to save. Press **Menu** when done to return to Main screen.



1620 Hawkins Avenue, Sanford, NC 27330 • (919) 566-8000
10951 W. Los Angeles Avenue, Moorpark, CA 93021 • (805) 553-5000

(800) 831- 7133 – Fax (800) 284-4151

©2007 Pentair Water Pool and Spa, Inc. All rights reserved.

P/N 520922 Rev. A 5/30/07